

## **CVT502, CVT506 DC/Battery Voltage Trip Relays**



- **DC/battery voltage** monitoring, 12 or 24V
- Adjustable trip level
- Compact DIN rail/ surface mount case

#### **Description**

These units are similar to the CVT500 series of general purpose trip relays, but have been adapted to monitor the voltage of their own DC supply. The trips are suited to applications where an auxiliary supply is either unavailable or undesirable, for instance when monitoring the float voltage of an engine or standby generator battery supply.

Each unit incorporates a two pole change-over relay with volt-free contacts. The relay de-energises when the supply/input voltage falls below the trip level, as set by the user on a screwdriver adjustable potentiometer in the front facia. The front facia also features an LED indicator which lights when the relay is energised (when the input voltage is above the trip level).

Electrical connection is via screw teminals in the case front, for use with stripped wires or narrow blade crimps. The CVT uses a compact, robust polycarbonate case, designed for DIN rail or surface mounting.

#### Warranty

A two year limited warranty on materials and workmanship is given with this Murphy product. Details are available on request and are packed with each unit.


#### **How to Order**

Stock number Model - description 41.70.0007 CVT502 - DC voltage relay, 18 - 32V 41.70.0040 CVT506 - DC voltage relay, 9 - 16V

#### **Specification**

	CVT502	CVT506
Power supply:		
operating voltage, VDC	18 – 40	9 – 20
power consumption, W	< 0.15	< 0.3
Control:	40.00	0 40
trip adjustment range, VDC	18 – 32	9 – 16
Relay output:	DPDT volt free contacts rated 5A max. @ 240V AC (resistive load) 2 x 10 <sup>5</sup> operations	
General:		
operating temperature	–10 to +55°C	
weight	approx. 210 g	
dimensions (w x h x d)	50 x 75 x 110 mm	

#### Connection



# murphy

#### **FWMurphy**

PO Box 470248 Tulsa, Oklahoma 74147, USA tel: (918) 627 3550 fax: (918) 664 6146 email: sales@fwmurphy.com web: www.fwmurphy.com

### CONTROL SYSTEMS AND SERVICES DIVISION

PO Box 1819, Rosenberg, Texas 77471, USA tel: (281) 342 0297 fax: (281) 341 6006 email: sales@fwmurphy.com

#### MURPHY DE MEXICO S.A. DE C.V.

Blvd. Antonio Rocha Cordero 300, Fracción del Aguaje San Luis Potosí, S.L.P. México 78384 tel: + 52 444 8206264 fax: + 52 444 8206336

email: ventasmex@murphymex.com.mx web: www.murphymex.com.mx

#### FRANK W. MURPHY LTD.

Church Rd, Laverstock, Salisbury, SP1 1QZ, UK tel: +44 1722 410055 fax: +44 1722 410088

email: sales@fwmurphy.co.uk web: www.fwmurphy.co.uk

#### MURPHY SWITCH OF CALIFORNIA

41343 12th Street West, Palmdale, CA 93551-1442, USA tel: (661) 272 4700 fax: (661) 947 7570 email: sales@murphyswitch.com web: www.murphyswitch.com

#### MACQUARRIE CORPORATION

1620 Hume Highway, Campbellfield, Victoria 3061, Australia fax: +61 3 9358 5558 email: murphy@macquarrie.com.au

